## **SPECIFICATION** STICK-DE3

PROJECT	DATE
TYPE	QTY



#### TOUCH SENSITIVE INTELLIGENT CONTROL KEYPAD

# **INTELLIGENT SERIES**



STICK-DE3

#### **DESCRIPTION:**

The feature rich lighting controller has been designed to provide a control solution for the most demanding of projects, while maintaining an easy to use panel of touch sensitive buttons. The controller integrates a graphic color screen allowing scene photos to be displayed. Easily view the selected zone, scene name and design without the need to navigate through complex menus. Change the speed, color and dimmer using the circular palette.

The lighting levels, color and effects can be programmed from a PC, Mac, Android, iPad or iPhone using the included software.

#### **FEATURES:**

- Sleek glass design which sits 11mm from the wall
  Graphic color display to show selected environment
- Color/dimmer/speed palette
- Color temperature mixing
- Touch sensitive buttons. No mechanical parts
- Touch sensitive wheel allows for accurate color selection
- Multi-zone microSD memory
- Multi-room control with 500 scenes, 10 zones
- 1024 DMX channels. Control 340 RGB fixtures
- USB & Ethernet connectivity for programming and control
- RS232, Dry Contact Ports and an Infra Red input port
- Clock and calendar with Sunrise/Sunset triggering
- Network communication. Control lighting remotely
- Catalog of designs including black and white glass
- OEM customization of the color palette and logo
- Windows/Mac software to set dynamic colors/effects
- iPhone/iPad/Android remote and programming apps

#### **SPECIFICATIONS**

MODEL	STICK-KE1
Input Power	6-7V DC 0.6A
Output Protocol	DMX512 (x2)
Program Platforms	PC, Mac, Tablet, Smartphone
Housing Color	Black / White
Connections	USB, Ethernet, RS232, Clock, 8 dry contact ports, Output Relay
Memory	MicroSD Card (32Gb Max)
Battery	LIR2032
Temperature	-10 °C to 45 °C
Mounting	Single or double gang wall socket
Dimensions	146x106x11mm
Weight	247g
Standards	EC, EMC, ROHS, ETL

ORDERING Example: STICK-DE3-POWER4M Stick-DE3 Controller with a 6V ACDC Power Supply

### **MODEL**

STICK-DE3

Stand alone wall-mounted DMX controller

#### **ACCESSORIES**

RJ2BLOCK - RJ45 to connector block converter for power & DMX POWER4M - 6V ACDC Power Supply

epiXsky